



## Control Remoto largo alcance 300 m - 12 Botones Doble Velocidad - Multivoltage

### Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Servicio y Atención al Cliente en Chile

### Especificaciones Técnicas

<b>Codigo FCC</b>	2AZMK-Q1212	<b>Código de Seguridad</b>	200 Millions
<b>Capacidad Contactor</b>	10A	<b>Potencia del Transmisor</b>	≤10dBm
<b>Botones</b>	13	<b>Rango de Frecuencia</b>	433/480 MHz
<b>Fuente de Alimentación del Transmisor</b>	2 AA batteries	<b>Parada de Emergencia</b>	YES
<b>Material</b>	PA6 30% GF	<b>Rango de temperatura de Trabajo</b>	-40 ~ 185 °F / -40 ~ 85°C
<b>Fuente de Alimentación del Receptor</b>	AC 110V-480V	<b>Normas</b>	FCC and OSHA standard 1910.179
<b>Sensibilidad del Receptor</b>	dBm -112	<b>Garantía</b>	1 Year
<b>Distancia de Control</b>	900 ft / 300 mt		

## Peso & Dimensiones

<b>A Altura Total</b>	8
<b>W Ancho</b>	2.1"
<b>D Depth</b>	0.6"
<b>Peso Total</b>	6 lbs / 3 Kg

## Detalles del Empaque

<b>Paquete 1 Peso Neto</b>	6 lbs / 3 Kg
<b>Paquete 1 Ancho</b>	8 in / 20.32 cm
<b>Paquete 1 Peso Bruto</b>	6 lbs / 3 Kg
<b>Paquete 1 Altura</b>	5 in / 12.7 cm
<b>Paquete 1 Profundidad</b>	12 in / 30.48 cm

Referential Images / Imágenes Referenciales  
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso